



Commercial
Electric

LED ALUMINIUM SECURITY LIGHT

MANUAL – MODEL NO. CELEDSLA



2YEAR
Replacement
Warranty



Please read the operating instructions carefully prior to use. Please retain the instructions in a safe place for future reference.

INTRODUCTION

Congratulations on the purchase of your new Commercial Electric LED Aluminium Security Light.

Before first using, it is most important that you read and follow the instructions in this manual, even if you feel you are quite familiar with this type of product.

Your attention is drawn particularly to the section dealing with “IMPORTANT SAFEGUARDS”. Find a place and keep this booklet handy for future reference.

SPECIFICATIONS

Model no.:	CELEDSLA
Power Source:	AC 220-240V ~ 50Hz
Power Consumption:	3.2 Watts
Waterproofing:	IP44
Protection Class:	Class I
Lamp:	2 LED Lights

IMPORTANT SAFEGUARDS

WHEN USING ELECTRICAL APPLIANCES, IN ORDER TO REDUCE THE RISK OF FIRE, ELECTRIC SHOCK, AND/OR INJURY, THESE BASIC SAFETY PRECAUTIONS SHOULD ALWAYS BE FOLLOWED:

FOR YOUR SAFETY

Read all instructions carefully, even if you feel you are quite familiar with the appliance.

- Any alterations or additions to building wiring, must be completed by a licensed electrical mechanic, or person authorised by legislation to work on the fixed wiring of any electrical installation.
- To prevent electric shock, please ensure that power is disconnected before installing.
- The appliance is not intended for use by children or infirm persons without supervision.
- Children should be supervised to ensure that they do not play with the appliance.
- This unit must be connected to a 220v ~ 240v 50Hz power source.
- The lamp must be earthed.
- The cable installed shall be $3 \times 1.0\text{mm}^2$ at least..
- The lampshade is not permitted to be opened.
- The lamp is for outdoor use only.
- The lamp is for wall mounting.

COMPULSORY WARNING

Note: No user serviceable parts inside. The LED's in the light can not be replaced. Unauthorised modification voids warranty. Return to place of purchase for replacement or service under warranty.

SAVE THESE INSTRUCTIONS

INSTALLATION

Note: It is illegal for persons other than licensed electricians, or persons authorised by legislation to work on the fixed wiring of any electrical installation.

STEP 1.

- Position mounting bracket against the wall and mark the positions for the screws.
- Note that the screw holes have rubber inserts to provide a weatherproof seal on the rear of the mounting bracket.

NOTE: There is a water outlet in the cover part of the mounting bracket. Ensure to mount the bracket following the “UP” arrow direction.

STEP 2.

- Using a power drill, drill into the wall to provide a suitable mounting for the screws. Care should be taken to avoid drilling or screwing into concealed electrical cables.
- For solid brick walls, we suggest that screws and masonry plugs are used.
- Fix the mounting bracket to the wall, feeding the supply cable through far enough to allow connection.

STEP 3.

- Wire the fitting in accordance with AS/NZ 3000. (see Wiring Instructions)
- Connect the fitting to a 220V - 240V 50Hz power source.
- Check all wiring connections, ensuring all connections have been tightened securely.

STEP 4.

- Ensure wires do not obstruct the mounting screws.
- Attach the fitting to the mounting bracket with the two screws and washers.

CLEANING

- Before cleaning, the power is cut off, and allow to cool before commencing.
- Care must be taken while cleaning to avoid scratching the fitting. A soft clamp cloth, or a fine hair brush should be used with a non-abrasive cleaner.
- DO NOT use solvents, or abrasive cleaners on any part of your Commercial Electric LED Aluminium Security Light.

WIRING INSTRUCTIONS

1. Feed the cable through the back mounting box and insert the cable entry to avoid abrasion to the cable.
2. Connect the earth wire to the connector opposite the green/yellow cable. (See Fig. 1).
3. Connect the live wire (red phase conductor) to the connector opposite the brown cable.
4. Connect the black neutral conductor to the connector opposite the blue cable.
5. Check that all the connections are correct and tight.
6. Re-install the fitting to the back mounting box.




Fig 1

CONTENTS

1 X LED Aluminium Security Light
2 x Wall Mounting Screws

2 x Wall plugs

PRODUCT WARRANTY

2 YEAR REPLACEMENT WARRANTY

Your Commercial Electric product is covered for a Period of 24 months from the **ORIGINAL Date of purchase.**

The Warranty covers faulty parts or workmanship.

The warranty is only made available by returning the product to your point of purchase with a **confirmed cash register receipt.**

PURCHASED FROM:

DATE OF PURCHASE:

THIS WARRANTY FORM SHOULD BE RETAINED BY THE CUSTOMER AT ALL TIMES.

WARNING

The following actions will result in the warranty being void:

- If the product has been operated on a supply voltage other than that specified on the unit.
- If the product shows signs of damage or defects caused by or resulting from abuse, accidents or alterations.
- If the product has been disassembled or tampered with in any way.
- If the product is not drilled, mounted and used in accordance with the instructions.

Note: Warranty excludes consumable parts such as tubes, globes, batteries and all accessories.

YOUR WARRANTY FORM SHOULD BE RETAINED BY YOU AT ALL TIMES.

SHOULD YOU HAVE ANY QUESTIONS PRIOR TO RETURNING YOUR PRODUCT FOR WARRANTY OR REPAIR PLEASE TELEPHONE OUR CUSTOMER SERVICE HELPLINE:

**Australia 1800 069 486
New Zealand 0508 069 486**

TO ENSURE A SPEEDY RESPONSE PLEASE HAVE THE MODEL NUMBER AND DATE OF PURCHASE AVAILABLE. A CUSTOMER SERVICE REPRESENTATIVE WILL TAKE YOUR CALL AND ANSWER ANY QUESTIONS YOU MAY HAVE RELATING TO THE WARRANTY POLICY OR PROCEDURE.

Commercial Electric

5 Chestnut Crt, Dingley, Vic, Australia, 3172

Telephone: 03 9558 3999

Facsimile: 03 9558 0583

www.commercialectric.com.au